DCN-DVCS-xx Delegate Unit with Voting and Channel Selector

www.boschsecurity.com





- ▶ Low susceptibility to mobile phone interference
- ▶ Compact, attractive and ergonomic design
- ► Five voting buttons, built-in loudspeaker and pluggable microphone
- Channel selector with number and abbreviated channel name
- ▶ Usable as a delegate unit or as a chairman unit

The Delegate Unit with Voting and Channel Selector enables participants to speak, register a request-to-speak, listen to the speaker and vote. A socket is provided to connect the pluggable microphones (DCN-MICS and DCN-MICL, to be ordered separately). The unit has five voting buttons for all types of voting. The yellow indicators above the voting buttons are used to prompt users to register their presence, to start voting and to confirm their vote. When the unit's attendance LED is yellow, it indicates the delegate is present.

The unit has a built-in channel selector, which makes it suitable for discussions in which more than one language is used and simultaneous interpretations are available. The channel selector includes up and down channel select keys and a display showing the number and the abbreviation of the languages, enabling rapid selection of the required language channel.

Functions

• Headphone output level reduction to prevent acoustic feedback (active when listening to the floor and when the microphone is on).

- The built-in loudspeaker is muted when the microphone is on to prevent acoustic feedback
- The unit can be used as a delegate unit, as a chairman unit (DCN-DBCM chairman buttons to be ordered separately) or as a delegate unit with auxiliary button. The versatile auxiliary button can be used as an usher call, for example
- To lock the loop-through cable, a cable clamp is available (DCN-DISCLM, to be ordered separately)

Controls and Indicators

- · Five voting buttons with indicator above the buttons
- Unit activity/delegate presence indicator
- Alphanumeric display for language channel selection with number and abbreviated channel name
- Microphone button with a red, green or yellow illuminated LED. Red indicates microphone is active, green indicates request-to-speak accepted, and yellow indicates 'VIP'.
- VIP indicator is lit when the delegate is part of the notebook (only available if PC Software is used)
- Headphones volume control buttons
- Recessed 'De-init' switch

Interconnections

Socket for pluggable microphone

- Two 3.5 mm (0.14 in) stereo jack type headphone sockets
- 2 m (78.7 in) cable terminated within a molded six-pole circular connector
- Six-pole circular connector for loop-through connections

Technical specifications

Electrical

Frequency response	30 Hz to 20 kHz
Headphone load impedance	> 32 Ohm < 1k Ohm
Output power	2 x 15 mW/32 Ohm

Mechanical

Mounting	Tabletop (portable or fixed mounting)
Dimensions (H x W x D)	(without microphone)
Tabletop	60 x 210 x 140 mm (2.36 x 8.27 x 5.51 in)
Weight	1.15 kg (2.54 lb)
Color top	Black (RAL 9017)
Color rear	Silver (RAL 9006)

Ordering information

DCN-DVCS-CN Delegate Unit with Voting, Channel Selector (CN)

With voting and channel selector (Chinese version). Order number **DCN-DVCS-CN**

DCN-DVCS Delegate Unit with Voting, Channel Selector

With voting and channel selector.

Order number DCN-DVCS

Accessories

DCN-MICS Pluggable Short Microphone

length 310 mm (12.2 inch), silver Order number **DCN-MICS**

DCN-MICS-D Pluggable Short Microphone Dark

length 310 mm (12.2 inch), dark Order number **DCN-MICS-D**

DCN-MICL Pluggable Long Microphone

length 480 mm (18.9 inch), silver Order number **DCN-MICL**

DCN-MICL-D Pluggable Long Microphone Dark

length 480 mm (18.9 inch), dark Order number **DCN-MICL-D**

DCN-DBCM Buttons Chairman (10 sets)

10 Sets

Order number DCN-DBCM

DCN-DISCLM Cable Clamp (25 pcs)

25 pieces

Order number DCN-DISCLM

Represented by:

Americas:

Americas: Bosch Security Systems, Inc. 12000 Portland Avenue South Burnsville MN 55337, USA Phone: +1-800-392-3497 Fax: +1-800-955-6831 audiosupport@us.bosch.com www.boschsecurity.com

Europe, Middle East, Africa:

Bosch Security Systems B.V. P.O. Box 80002 P.O. Box 80002 5617 BA Eindhoven, The Netherlands Phone: + 31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com www.boschsecurity.com

Asia-Pacific:

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

China:
Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398 www.boschsecurity.com.cn

America Latina:

America Latina:
Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
al.securitysystems@bosch.com
www.boschsecurity.com