# DCN-DISCS Discussion Unit with Channel Selector

www.boschsecurity.com





The Discussion Unit with Channel Selector enables participants to speak, register a request-to-speak and listen to the speaker. A socket is provided to connect the pluggable microphones (DCN-MICS and DCN-MICL, to be ordered separately). The unit has a built-in channel selector that makes it suitable for discussions in which more than one language is used and simultaneous interpretations are available. The channel selector includes two up and down channel select keys and a display showing the number and the abbreviation of the languages, enabling rapid selection of the required language channel.

# Functions

- Headphone output level reduction to prevent acoustic feedback (active when listening to the floor and when microphone is on)
- The built-in loudspeaker speaker is muted when the microphone is on to prevent acoustic feedback.
- A variety of rims (DCN-DISR, to be ordered separately) are available, so the unit can be matched to the interior

- ▶ Low susceptibility to mobile phone interference
- Compact, attractive and ergonomic design
- Pluggable microphone
- Channel selector with number and abbreviated channel name
- Built-in loudspeaker

- The unit can be used a delegate unit or as a chairman unit (DCN-DISBCM chairman buttons, to be ordered separately)
- To lock the loop-through cable, a cable clamp is available (DCN-DISCLM, to be ordered separately)
- The unit is available in light and dark colored bases

## **Controls and Indicators**

- Alphanumeric display for language channel selection with number and abbreviated channel name
- Socket for pluggable microphones (DCN-MICS or DCN-MICL)
- Microphone button with a red, green or yellow illuminated ring. Red indicates microphone is active, green indicates request-to-speak accepted, and yellow indicates 'VIP'
- VIP indicator is lit when the delegate is part of the notebook (only available if PC Software is used)
- Headphones have volume control buttons
- Recessed 'De-init' switch

# Interconnections

- Socket for pluggable microphone
- Two 3.5 mm (0.14 in) stereo jack type headphones sockets

- 2 m (78.7 in) cable terminated with in a molded sixpole circular connector.
- Six-pole circular connector for loop-through connections

#### **Certifications and approvals**

Region	Certification
Europe	CE

# **Technical specifications**

# Electrical

Mechanical		
Output power	2 x 15 mW/32 ohm	
Headphone load impedance	> 32 ohm < 1k ohm	
Frequency response	30 Hz to 20 kHz	

Mounting	Tabletop (portable or fixed mounting) and flush mounting
Dimensions (H x W x D)	(without microphone)
Tabletop	61 x 190 x 116 mm (2.4 x 7.5 x 4.6 in)
Flush mounted	6 x 190 x 120 mm (0.2 x 7.5 x 4.7 in)
Weight	800 g (1.76 lb)
Color top	Silver (RAL 9022)
Color base	
DCN-DISCS-L	Light Grey (RAL 000 7500)
DCN-DISCS-D	Charcoal (PH 10736)

# **Ordering information**

# **DCN-DISCS-L Discussion Channel Selector Light**

pluggable microphone, light base, microphone and rims to be ordered separately Order number **DCN-DISCS-L** 

DCN-DISCS-D Discussion Channel Selector Dark pluggable microphone, dark base, microphone and rims to be ordered separately Order number DCN-DISCS-D

**DCN-MICS Pluggable Short Microphone** length 310 mm (12.2 inch), silver Order number **DCN-MICS** 

**DCN-MICL Pluggable Long Microphone** length 480 mm (18.9 inch), silver Order number **DCN-MICL** 

DCN-DISRH-SR Rim High Gloss Silver (10 pcs) silver, high gloss, 10 pieces Order number DCN-DISRH-SR DCN-DISR-SR Rim Silver (10 pcs) silver, 10 pieces Order number DCN-DISR-SR

DCN-DISR-D Rim Dark (10 pcs) dark, 10 pieces Order number DCN-DISR-D

**DCN-DISRMH Rim Metal High Gloss (10 pcs)** metal, high gloss, 10 pieces Order number **DCN-DISRMH** 

DCN-DISRMS Rim Metal Semi Gloss (10 pcs) metal, semi gloss, 10 pieces Order number DCN-DISRMS

DCN-DISBCM Buttons Chairman (10 sets) 10 sets Order number DCN-DISBCM

DCN-DISBDD Buttons Dual Use (10 sets) 10 sets Order number DCN-DISBDD

DCN-DISCLM Cable Clamp (25 pcs) 25 pieces Order number DCN-DISCLM

#### Represented by:

#### Americas:

Americas: Bosch Security Systems, Inc. 12000 Portland Avenue South Burnsville MN 55337, USA Phone: +1-800-392-3497 Fax: +1-800-955-6831 audiosupport@us.bosch.com www.boschsecurity.com

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002

P.O. Box 80002 5617 BA Eindhoven, The Netherlands Phone: + 31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com www.boschsecurity.com

@ Bosch Security Systems 2013 | Data subject to change without notice 1780660875 | en, V4, 03. Jun 2013

Asia-Pacific:

Asia-Pacific: Robert Bosch (SEA) Pte Ltd, Security Systems 11 Bishan Street 21 Singapore 573943 Phone: +65 6571 2808 Fax: +65 6571 2609 apr.securitysystems@bosch.com www.boschsecurity.asia

## China:

China: Bosch (Shanghai) Security Systems Ltd. 201 Building, No. 333 Fuquan Road North IBP Changning District, Shanghai 200335 China Phone +86 21 22181111 Fax: +86 21 22182398 www.bacsbecurity.com.cn www.boschsecurity.com.cn

#### America Latina:

America Latina: Robert Bosch Ltda Security Systems Division Via Anhanguera, Km 98 CEP 13065-900 Campinas, Sao Paulo, Brazil Phone: +55 19 2103 2860 Fax: +55 19 2103 2862 al.securitysystems@bosch.com www.boschsecurity.com